

CHIAYO



COACH PRO 500

Personal Wireless PA System

COACH PRO 500

Personal Wireless PA System



COACH PRO, integrated with high-performance lithium battery, eliminates tangled cables and offers 3.5Ø audio input/output. Available echo control for wired and wireless microphone. Modern, stylish, compact as well as highly functional.

FEATURES

- 55W Class-D power amplifier.
- 5 ½" full range speaker.
- Optional receiver module with 16 frequencies.
- MP3 player & recorder (USB jack) with LCD screen and remote control.
- 6.3mm jack connector for microphone input.
- AUX IN (3.5mm jack).
- AUX OUT (3.5mm jack) for external audio recording.
- ECHO with bypass for wired and wireless microphones.
- Two alarm buttons for emergency broadcasting.
- Up to 12 hours operating time per charge with lithium battery.
- Battery compartment design for simple battery replacement.



Small but loud

Built-in 55W class-D power amplifier drives 5 1/2" full range speaker and easily satisfies the amplification requirement of small events with a 100-300 crowd.



Best take-and-go

Easy to carry around by hand or shoulder, or mounted on a tripod. It is the best companion for small venues such as religious gatherings, guided tours, electoral campaigns, teaching and presentation of exhibitions.



Flexible customization

The multimedia functions are flexibly expandable based on the requirement of various applications, such as the receiver module of wireless microphone and MP3 recorder player with remote control.



Long battery duration

12 hours of operation per charge. Battery compartment design makes battery replacement much easier.



Comtatible



SQ-5116
Rechargeable Handheld
Wireless Microphone



SQ-1016V
Rechargeable Handheld
Wireless Microphone



SQ-1016
Rechargeable Handheld
Wireless Microphone



Q-5001
Rechargeable
Handheld Wireless
Microphone



Q-818
Handheld Wireless
Microphone



SM-2016
Rechargeable
Belt-pack Transmitter



M-818
Rechargeable
Belt-pack Transmitter

Accessories



ST-30
Tripod stand



12W0038
Lithium battery (16.8V
2.6A)



SB-61
Carrying bag

COACH PRO 500

Max power output	55W, 3Ω load (class-D)
Speaker system	5 ½" full range
Frequency response	50Hz-20KHz±3dB
T.H.D.	< 0.5%
Audio input	MIC in (Ø6.3mm), AUX in (Ø3.5mm), USB (optional)
Audio output	AUX out (Ø3.5mm)
Power supply	100-240V AC, 19V DC / 3.42A
Battery	Lithium (16.8V/2.6Ah)x1
Operating time	5-6 hours in music, 10-12 hours in speech
Charging time	about 4 hours
Dimensions (mm)	162 x 292 x 184
Weight (kg)	2.2



CHIAYO CHIAYO ELECTRONICS CO., LTD.

Office : No.30, Lane 27, Sec. 4, Jen-Ai Rd, Taipei 10685, Taiwan TEL : 886-2-2741-5741 FAX : 886-2-2752-5242

Factory : No.88, Chung-Hsiao St. 2, Chiayi 60080, Taiwan TEL : 886-5-271-1000 FAX : 886-5-276-7611

International enquiries : sales@chiayo.com.tw or call **+886 2 2741 5741** www.chiayo.com.tw